

Self-contained Carbon Monoxide Alarm

Model SF350EN

The world's first
European Approved
Carbon Monoxide Alarm



**Produced by SF Detection,
Europe's No. 1 manufacturer of
Carbon Monoxide alarms.**

**Why choose the SF350EN Carbon
Monoxide (CO) alarm:**

- 5 year guarantee
- Superior electrochemical cell sensing technology
- Easy to use and install
- Automatic sensor adjustment function ensures complete accuracy
- Approved to EN50291:2001 and Kite marked
- Continuous self-test function
- Batteries supplied and pre-fitted in alarm
- No sensors to replace
- No mains power required
- No maintenance



EURO-GAS MANAGEMENT SERVICES LTD, REVELSTOKE HOUSE,
STOKE ROAD, NOSS MAYO, PLYMOUTH, DEVON PL8 1EY, UK

☎: +44 (0)1752 872222 Fax: +44 (0)1752 872223

euro-gas@btconnect.com www.euro-gasman.com

EURO-GAS
MANAGEMENT SERVICES LTD

Carbon Monoxide Alarm

Model SF350EN

Specification

Detection Principle:	Electrochemical cell
Operating Voltage:	4.5V
Alarm Life:	5 years under normal operation conditions
End of Alarm Life Warning:	3 short chirps every minute
Alarm Indication:	Audible & visual alarm
Buzzer Output:	>85 decibels at 3m
Operating Temperature:	-10 - +40°C
Alarm Levels:	50ppm between 60-90 minutes 100ppm between 10-40 minutes 300ppm <3 minutes (as required by EN50291:2001)
Weight:	140g approx.
Dimensions:	110mm x 76mm x 34mm
Test Facility:	Yes
Self-Check Function:	Yes



Sensor Technology

The latest electrochemical cell technology ensures complete accuracy and reliability, giving a 5 year guaranteed life under normal operating conditions. It is officially approved and Kite marked to the stringent performance requirements of EN50291:2001 – the European Standard for domestic Carbon Monoxide alarms. It is also officially approved by CORGI.



Installation

The SF350EN is easily attached using the fixing kit provided, with no need for any wiring. No maintenance is required for the full 5 year life of the alarm, with no sensors or any parts to replace.

Maintenance-free Operation

This alarm, including batteries, is guaranteed for 5 years. Battery replacement is therefore not required for the whole life of the alarm.

All gas appliances should be checked for safety annually.

Please Note: Whilst every effort has been made to ensure accuracy in this publication, no responsibility can be accepted for errors or omissions. Data may change, as well as legislation, and you are strongly advised to obtain copies of the most recently issued regulations, standards and guidelines.

